

ACTIV MENU SETTINGS

Recommended settings for :
Doremi



SERVER SETTINGS: From the Doremi menu system set protocol settings as required.
Note - controller VDCP settings - all port ids set to 1.

Software version [] Serial number []

Open menu, from CLIP LIST press SHIFT + ENTER
or for Cartbox, press SHIFT + S5

VDCP

PARAMETER	RECOMMENDED VALUE	YOUR SETTINGS	LOCATION
DEVICE TYPE	<i>Set as required</i>	[]	CHANNEL MENU
VIDEO PORT NUMBER	1	[]	
DISK PROTOCOL	VDCP		DISK MENU
TIMECODE	<i>Set as required</i>	[]	
GOTO COMMAND	JOG	[]	
VARIABLE ID LENGTHS	ON	[]	
PLAYLIST LOAD	00:00:05:00	[]	
PLAYLIST CHANGE	00:00:00:16	[]	
CUE END LATENCY	00:00:00:01	[]	
LOAD LATENCY	5 frames	[]	
VIDEO STANDARD	<i>PAL / NTSC</i>	[]	SYSTEM MENU
LICENCE OPTIONS	<i>View enabled options</i>		

ODETICS

DEVICE TYPE	<i>Set as required</i>	[]	CHANNEL MENU
DISK PROTOCOL	ODETICS		DISK MENU
TIMECODE	<i>Set as required</i>	[]	
PLAYLIST LOAD	00:00:05:00	[]	
CUE END LATENCY	00:00:00:01	[]	
EJECT DELAY	200 mSec	[]	
CUE COMMAND	NEW (44 14)	[]	
VIDEO STANDARD	<i>PAL / NTSC</i>	[]	SYSTEM MENU
LICENCE OPTIONS	<i>View enabled options</i>		

VTR

DEVICE TYPE	VTR		CHANNEL MENU
TIMECODE	<i>Set as required</i>	[]	VTR MENU
FRAME OFFSET	00:00:00:02	[]	
CUE END LATENCY	00:00:00:01	[]	
LIVE TC SOURCE	TC GEN	[]	
VIDEO STANDARD	<i>PAL / NTSC</i>	[]	SYSTEM MENU
LICENCE OPTIONS	<i>View enabled options</i>		